

SIP- LinkSys SPA-2102

SIP- LinkSys SPA-2102 Web- :

1. «Ethernet» SIP . IP- SIP- Wan Setup, (Enable WAN web server – yes,).



LINKSYS®
A Division of Cisco Systems, Inc.

Linksys Phone Adapter Configuration

Router | Voice

Status | **Wan Setup** | Lan Setup | Application

User Login | basic | advanced

Internet Connection Settings

Connection Type: Static IP

Static IP Settings

Static IP: 192.168.0.155 NetMask: 255.255.255.0

Gateway: 192.168.0.1

PPPoE Settings

PPPoE Login Name: PPPoE Login Password:

PPPoE Service Name:

Optional Settings

HostName: Domain:

Primary DNS: Secondary DNS:

DNS Server Order: Manual DNS Query Mode: Parallel

Primary NTP Server: Secondary NTP Server:

MAC Clone Settings

Enable MAC Clone Service: no Cloned MAC Address:

Remote Management

Enable WAN Web Server: yes WAN Web Server Port: 80

QoS Settings

QoS QDisc: NONE Maximum Uplink Speed: 128 (Kbps)

VLAN Settings

Enable VLAN: no VLAN ID: 1 [0x000-0xFFFF]

Undo All Changes Submit All Changes

«Ethernet» SIP , , «Bridge», **LAN Setup**, «Internet». IP , Line1 , ****, 210 #. IP – **** 110 #.

2. SIP Line1

Router		Voice	
Info	System	SIP	Provisioning
Regional	Line 1	Line 2	User 1
User 2	User Login	Basic	Advanced

SIP Settings

SIP Port:	5060	SIP 100REL Enable:	no
EXT SIP Port:		Auth Resync-Reboot:	yes
SIP Proxy-Require:		SIP Remote-Party-ID:	yes
SIP GUID:	no	SIP Debug Option:	1-line
RTP Log Intvl:	0	Restrict Source IP:	no
Referor Bye Delay:	4	Refer Target Bye Delay:	0
Referee Bye Delay:	0	Refer-To Target Contact:	no
Sticky 183:	no		

Call Feature Settings

Blind Attn-Xfer Enable:	no	MOH Server:	
Xfer When Hangup Conf:	yes	Conference Bridge URL:	
Conference Bridge Ports:	3		

Proxy and Registration

Proxy:	172.16.5.135
Outbound Proxy:	
Use Outbound Proxy:	no
Register:	no
Register Expires:	3600
Use DNS SRV:	no
Proxy Fallback Intvl:	3600
Voice Mail Server:	
Use OB Proxy In Dialog:	yes
Make Call Without Reg:	yes
Ans Call Without Reg:	yes
DNS SRV Auto Prefix:	no
Proxy Redundancy Method:	Normal
Mailbox Subscribe Expires:	2147483647

Subscriber Information

Display Name:	111	User ID:	111
Password:	*****	Use Auth ID:	yes
Auth ID:	111		
Mini Certificate:			
SRTP Private Key:			

Dial Plan

Dial Plan:	S0(:172.16.5.135)
Enable IP Dialing:	yes
Emergency Number:	