

GB/T28181

- [GB/T28181](#)
- [IP- GB/T28181](#)
- [IP- GB/T28181](#)

GB/T28181

Axxon Next GB/T28181.

SIP UDP (GB/T28181-2016 TCP). SIP GB/T28181 :

- SDP (Session Description Protocol)
- MANSCDP (Monitoring and Alarming Network System Control Description Protocol)
- MANSRTSP (Monitoring and Alarming Network System Real Time Streaming Protocol)

SIP- (), , , IP- (Axxon Next) .. UDP TCP.

OSI SIP RTP/RTCP, :

- (..) H264, H265 MJPEG;
- G.711a, G.711u, G.726 PS (Program Stream).

Axxon Next DriverPack – . [Documentation Drivers Pack](#).

IP- GB/T28181

IP-, GB/T28181, Web- IP-, Axxon Next .

IP- Axxon Next, SIP IP- :

1. Server IP IP- .
2. Server port (5060).
3. Device ID. , GB/T28181, . (ID ID) – 20- :
 - 10 (GB/T-2260-2007);
 - 10 .
4. RefreshRegTime , . IP- .



IP- RefreshRegTime 600.



[IP- GB/T28181](#)

IP- GB/T28181



!

IP- GB/T28181 SIP-, , IP- GB/T28181, @ .ID, , . - (, IP-,), .



Axxon Next GB/T28181 .

Axxon Next :

1. IP- ([IP-](#)).

2. IP- GBT28181 (1).

IP-адрес 2	Порт 3	Производитель 1	Имя пользователя
34020000001320000001	5060	GBT28181	Авто
Тип устройства	Модель	Пароль	
IP-устройство	1 channel device	****	

3. IP- Device ID, IP- (2).

deviceID[/videoPort][@localIP[/externalIP]]

deviceID[/videoPortFirst-videoPortLast][@localIP[/externalIP]]

:

deviceID – Device ID;

videoPort – ;

videoPortFirst-videoPortLast – ;

serverLocalIP – IP- Axxon Next, , ;

serverExternalIP – IP- Axxon Next, . IP- SIP- IP-.



34020000001320000008
 34020000001320000008@10.0.40.246/113.125.160.58
 34020000001320000008@10.0.40.246
 34020000001320000008@/113.125.160.58
 34020000001320000008/50200
 34020000001320000008/50200-50210@10.0.40.246

4. , Axxon Next IP- (3). SIP – 5060.



SIP- IP- .

5. (4).



6. .

GB/T28181 .